

MAIN FEATURES

Miniaturized encoder series for general factory automation applications, small AC motors and gearmotors.

- · 3 channel encoder (A / B / Z) with resolution up to 14400 ppr
- Power supply up to +30 V DC with several electrical interfaces available
- · Up to 500 kHz output frequency
- Cable output, connectors available on cable end
- Metal cover for high IP enclosure rating
- Blind hollow shaft diameter up to 10 mm with collar clamping
- · Mounting by stator coupling or torque pin







ORDERING CODE	ER	38F	500	S	5/30	P	10	X	X	PR	. XXX
ORDERING CODE	SERIES incremental encoder series ER blind hollow shaft with stator cou blind hollow shaft with torque	MODEL pling 38F e pin 38G RES from 100 e available	SOLUTION to 14400 pulses list ZEF without zer with zer	RO PULSE o pulse S o pulse S o pulse Z o POWER al interface) 5 30 V ELEC	SUPPLY 5 V DC 5 DC 5/30 TRICAL IN PN open c pu lin	ITERFACE OISH-pull P e driver L S-422 RS BORE D	JIAMETER mm 4 mm 5 mm 6,35 mm 8 mm 10		X	PR	. XXX
					IP 66		ENCLOSURI e / IP67 cov				
								to be re	OPTION eported X		
			nreferred o	ahle length	:15/2/3	1/5/10 m	radial c	able (stand	ard length		
			F. 0.004 C		,0 , _ , 0	. 3, 20 111,	50 00000		(08		VARIANT





custom version XXX



RECOMMENDED INTERFACE FLANGE DESIGN 38F







dimensions in mm

CONNECTIONS		
Function	Cable C / P	Cable L / RS
+V DC	red	red
0 V	black	black
A+	green	green
A-	/	brown or grey
B+	yellow	yellow
B-	/	orange
Z+	blue	blue
Z-	/	white
<u>+</u>	shield	shield

ELECTRICAL SPECIFICATIONS					
Resolution	from 100 to 14400 ppr				
Power supply ¹	$5 = 4.5 \dots 5.5 \text{ V DC}$ $5/30 = 4.5 \dots 30 \text{ V DC}$ (reverse polarity protection)				
Power draw without load typical	5 = 200 mW 5/30 = 800 mW				
Max load current	C/P = 50 mA/channel L/RS = 20 mA/channel				
Electrical interface ²	NPN open collector (AEIC-7273, pull-up max +30 V DC) push-pull / line driver HTL (AEIC-7272 or similar) line driver RS-422 (AELT-5000 or similar)				
Max output frequency	250 kHz up to 3600 ppr / 500 kHz from 4000 ppr				
Counting direction	A leads B clockwise (shaft view)				
Index signal	180°e (gated A)				
Mean time to dangerous failure (MTTF _d) ³ according to EN ISO 13849-1	263 years				
Mission time (Tm) ³	20 years				
Diagnostic coverage (DC) ³	0%				
Cable type	shielded - fixed installation conductors section 0,22 mm²/AWG 24 bending radius min 60 mm				
Electromagnetic compatibility	according to 2014/30/EU directive				
RoHS	according to 2011/65/EU directive				
UL / CSA	file n. E212495				

MECHANICAL SPECIFICATIONS			
Bore diameter	ø 4* / 5* / 6* / 6,35* (1/4") / 8* / 10 mm * with supplied shaft adapter		
Enclosure rating IEC 60529	IP 66 shaft side / IP 67 cover side		
Max rotation speed	6000 rpm		
Max shaft load ⁴	5 N (1,12 lbs) axial / radial		
Shock	50 G, 11 ms (IEC 60068-2-27)		
Vibration	10 G, 10 2000 Hz (IEC 60068-2-6)		
Moment of inertia	0,8 x 10 ⁻⁶ kgm² (19 x 10 ⁻⁶ lbft²)		
Starting torque (at +20°C / +68°F)	< 0,01 Nm (1,42 Ozin)		
Bearing stage material	aluminum		
Shaft material	stainless steel		
Shaft adapter material	bronze		
Housing material	painted aluminum		
Bearings	n.2 ball bearings		
Bearings life	10 ⁹ revolutions		
Operating temperature ^{5, 6}	-25° +85°C (-13° +185°F)		
Storage temperature ⁶	-25° +85°C (-13° +185°F)		
Weight	150 g (5,29 oz)		
1 1 1 1 1 1 1 1 1 1	11.10		

¹ as measured at the transducer without cable influences

RESOLUTIONS

100 - 120 - 128 - 150 - 200 - 240 - 250 - 256 - 300 - **360** - 400 - 480 - **500** - **512** - 600 - 625 -720 - 800 - 900 - **1000 - 1024** - 1200 - 1250 - 1440 - 1600 - 1800 - **2000 - 2048 - 2500 -**3000 - **3600** - 4000 - 4096 - **5000** - 6000 - **7200** - 8000 - 8192 - 10000 - 12000 - 14400

please directly contact our offices for other pulses, preferred resolutions in bold





 $^{^{\}rm 2}$ for further details refer to OUTPUT LEVELS on TECHNICAL BASICS section

 $^{^{\}rm 3}$ this product is not a safety component, for further details refer to TECHNICAL BASICS section

⁴ maximum load for static usage

⁵ measured on the transducer flange

⁶ condensation not allowed